

# LED VALUE MR16 50 / MR16 35 / MR16 20

Low-voltage LED reflector lamps MR16



CRI  
80

## LED VALUE MR16 50 / MR16 35 / MR16 20

Product Name	GTIN (EAN)	wΔW	Beam	W	lm <sup>1</sup>	cd	K	Ra	Beam <sup>2</sup>	△	l [mm]	d [mm]	t [h] <sup>3</sup>	No.	No.
<b>LED VALUE MR16 50</b>															
LV MR16 50 36 5.5W/827 12V GU5.3	4058075588158	50	GU5.3	5.5	500	1,000	2,700	80	–	36°	44	50	15,000	10	1
LV MR16 50 36 5.5W/830 12V GU5.3	4058075588196	50	GU5.3	5.5	500	1,000	3,000	80	–	36°	44	50	15,000	10	1
LV MR16 50 24 5.5W/827 12V GU5.3	4058075588219	50	GU5.3	5.5	500	1,500	2,700	80	–	24°	44	50	15,000	10	1
<b>LED VALUE MR16 35</b>															
LV MR16 35 36 4.5W/827 12V GU5.3	4058075587571	35	GU5.3	4.5	400	720	2,700	80	–	36°	46	51	15,000	10	2
LV MR16 35 36 4.5W/840 12V GU5.3	4058075587618	35	GU5.3	4.5	420	720	4,000	80	–	36°	46	51	15,000	10	2
LV MR16 35 24 4.5W/827 12V GU5.3	4058075587694	35	GU5.3	4.5	400	1,200	2,700	80	–	24°	46	51	15,000	10	2
<b>LED VALUE MR16 20</b>															
LV MR16 20 36 3W/827 12V GU5.3	4058075587519	20	GU5.3	3	290	500	2,700	80	–	36°	46	51	15,000	10	2

<sup>1</sup> Typical values. All the technical parameters apply to the entire lamp. In view of the complex manufacturing process for light emitting diodes, the typical values given above for the technical LED parameters are merely statistical values that do not necessarily correspond to the actual technical parameters of an individual product; individual products may vary from the typical values

<sup>2</sup> LED lamps can be operated with a wide variety of commercially-available dimmers; details and results of compatibility tests can be seen at [www.ledvance.com/dim](http://www.ledvance.com/dim) and in the additional technical product information sheets linked there

<sup>3</sup> L70B50 is the average operating life of the LED Lamp during which the luminous flux is greater than or equal to 70% of the initial luminous flux, for 50% of the population. The lifetime is estimated at room temperature (25°C), free air burning, base up burning position and at rated voltage