

Instruction manual for 12V3A/5A power supply

1.Introduction

This power supply uses high quality electronic components and has been manufactured with advanced manufacturing technology.High product quality and reliability are guaranteed.

2.Scope of Operation

Suitable for building inter-coms,entrance and exit inhibitors,adn various electric door locks

3.Functions and Features

- 1.Input AC 220V/50Hz,output DC 12V stabilized 3A/5A
- 2.Direet control of door locks to reduce loading on door inhibitors,anti-disturbance,reduced wiring to save costs and reduce possible faults
- 3.N/O and N/C contacts for connection to various electric locks
- 4.Delayed switching,setttable between 0-15 seconds
- 5.Automatic protection. Power will be temporarily disconnected or fuse will blow when there is overloading or a short-circuit
- 6.Remote control with an optional remote control module. Aremote confroller is used to activate doors / gates. Control range is up to 80m at open field with no disturbance)

4.External Dimensions

88mm x 72mm x 30mm

5.Wiring terminals

- 1-2 Regulated output DC 12V, 1 is positive and 2 is negative.
- 3-7 Low frequency signal output .connect the signal line of access controller
- 5-6 NC-COM, Normally closed output DC 12V, trigger off, 6 is positive and 5 is negative.
- 4-5 NO-GND, Normally open without power output , 4 is positive and 5 is negative.

