



Available in 12 zone version, used for selecting speaker zone directly via the front panel or from remote paging console.

Features

- ❑ Available in 12 zones with ALL CALL.
- ❑ Expandable or cascadable to multiple zones.
- ❑ Remote zone triggering port via external paging mic.
- ❑ Paging override by KODIO paging console with priority override indicator.
- ❑ Emergency paging mic triggering port with dry contact for volume controller overriding application.
- ❑ Flexible amplifier – zone configurations.

Technical Specifications

Operating Voltage	24V DC via adaptor (optional)
Power consumption (AT ALL CALL)	6.8W; 0.28A
Zone load rating	500W at 100V amplifier line output
No of zone	12
No of amplifier inputs	12
Zone selection	Front panel & remote activation
Zone active indication	Front panel LEDs
Switching Mode	Individual or ALL CALL
Cable connection	Up to 2.5mm sq
Cable size	Up to 2.5mm sq
Dimension (W x H x D)	482 x 44 x 130mm
Weight (NET/PACKING)	1.75kg/2.20kg
Color	Back; powder epoxy coated