



RM5001 shall be used when a direct paging is required without having to select zone or when paging is to be made near rack which is installed with zone selector. It is also used as emergency paging console as a dry contact is available whenever the mic is active which is used to activate **ALL CALL** or overriding or as any other emergency contact.

Features

- Sensitive back electret condenser gooseneck mic with illuminated ring indicator.
- Mic activate with or without chime being broadcast.
- Chime & mic volume adjustment.
- Dry contact whenever mic is active for various purposes.
- Balanced mic output level for low noise transmission.

Technical Specifications

System	Condenser microphone with cardioid pattern
Operating Voltage	12V DC via adaptor
Power Consumption (at all call)	50mA
Output Level	Electronically balanced mic out 775mV
Output Impedance	600 Ohm
Output connection	¼" stereo phone jack
Chime	4 tone chime (Up & Down)
Frequency Response	100-12kHz (+/- 3dB; 0dB out)
Signal to noise ratio	60dB (@ 1KHz)
Indicators	Chime, Ready & Zone Select
Activation Dry Contact	3 A Relay
Operating Distance	Less than 100m
Dimensions (w) x (h) x (d)	150 x 186 x 62
Gooseneck mic length	440 mm
Weight (gms)	850
colour	Black