



**RM5006** shall be used when paging to specific zone is required in which the main rack is located away from the paging station.

### Features

- Sensitive electret condenser gooseneck mic with illuminated ring indicator.
- Mic activate with 4 tone chime.
- Chime & mic volume adjustment.
- 6 Zones selectors and ALL CALL with priority override for BGM muting at zone selector.
- Balanced mic output level for low noise transmission.

### Technical Specifications

System	Condenser microphone with cardioid pattern
Operating Voltage	24V DC
Power Consumption (at all call)	150mA
Output Level	Electronically balanced audio out 775mV
Output Impedance	600 Ohm
Output connection	¼" stereo phone jack for audio, 15 pin D female for data
Chime	4 tone chime (Up & Down)
Frequency Response	100-12kHz (+/- 3dB; 0dB out)
Signal to noise ratio	60dB (@ 1KHz)
Indicators	Chime, Ready & Zone Select
No. of zones selector	6 Zone with ALL CALL
Operating Distance	Up to 100m
Dimensions (w) x (h) x (d)	150 x 186 x 62
Gooseneck mic length	440 mm
Weight (gms)	900
Colour	Black