



Ex-Amplifiers AC/DC | Relay

Ex II (1) G [Ex ia Ga] IIC
 Ex II (1) D [Ex ia Da] IIIC

AC 230 V • AC 115 V • DC 24 V

Relay output


Cable break and short circuit monitoring

Turn off delay



Design **SZAb 400 EX...**

Dimensions



ID-No.	P11400	P11399	P11398
Type	SZAb 400 EX-WR230	SZAb 400 EX-WR115	SZAb 400 EX-GR
Output			
Supply voltage [V]	230 AC ±10%	115 AC ±10%	24 DC ±15%
Ex marking	Gas: Ex II (1) G [Ex ia Ga] IIC		Dust: Ex II (1) D [Ex ia Da] IIIC
Certificate No.	EPS 19 ATEX 1 009		IECEx EPS 19.0001
Maximum values	U _o = 13.65 V I _o = 200 mA P _o = 683 mW IIC: Co = 0.35 µF; Lo = 1.1 mH IIB: Co = 1.8 µF; Lo = 6.2 mH IIA: Co = 5.7 µF; Lo = 11.0 mH		
Turn off delay [s]	0...25		
Output	relay / change-over		
Switching voltage [V]	250 AC / 60 DC / 24 DC		
Switching current [A]	4 AC / 0.8 DC / 4 DC		
Switching power	cos φ >0,7 / L/R <200 ms		
Ambient temperature [°C]	-20 ≤ T _a ≤ +60		
Protection [EN 60529]	IP 20		
Connection	terminal screws		

Note:
 The Ex-amplifier must be mounted outside hazardous areas (gas or dust).

