



AREX SOLAR FLOODLIGHT LED BLACK – AR - SFL- 5W

Products Information:



Arex Solar Floodlight LED comes into two different working modes:

Sensor mode:

- When battery capacity above $>30\%$: Automatically turns on to full brightness when motion is detected in the range ≤ 6 mtrs, the dim to weak brightness in 20 seconds if no motion.



- When battery capacity below $<30\%$: Automatically turns on to full brightness when motion is detected in the range ≤ 6 mtrs, then turns off in 20 seconds if no motion.



Constant Lighting mode:

- Press the button for 3 seconds and shining one time, lamp turn to and lighting mode, both motion and light sensors disabled. Permanently keep lighting until the battery capacity reduces to zero switching back to Sensor mode.



Products Features:

- Zero Electricity
- PIR Detection
- Cordless
- Portable
- Battery Replacement



Application Area:

- Building wall, garden, Billboard, Pathway
- Street, Parking Lot, Courtyard

Wide application:

- Easily use it as wall light, floodlight , security light, camping light, portable light,
- Work light

INSTALLATION

1. Prepare the Lamp, accessories and tools well firstly.
2. Use the Allen wrench to loosen the bracket, adjust it to the appropriate angle and the fix the screw tightly.
3. Use the Allen wrench to loosen the light panel, pull it out and adjust to your demanded lighting angle, then fix the screw tightly.

PRODUCTS SPECIFICATIONS

Model:	AR-SFL-5W-3K AR-SFL-5W-6K	Product Code:	1023000011 (ww) 1023000012 (dl)
Wattage (W):	5W	Led Quantity:	30 pcs
Supply Voltage (V):	AC 2.8V-4.2V	Rated Lumen:	500 lm
Working currents(A):	1200mA	Lumen Efficiency:	100lm/w
CCT:	3000K 6500K	Beam Angle:	90 ⁰
CRI:	>80	Rated Life(L70):	35,000 Hours
Light Source:	SMD 2835	Barcode:	9 555106309454 (ww) 9 555106309591 (dl)
Operating Environment:	From -15°C to +45°C		