

Model: S25

Home & office security alarm system



Protect Your Property & Family
In Advanced & Intelligent Way

All about security & automation www.solidi.my



Technical Specifications

General Features

- * LCD keypad (4 Max number)
- * 448 event history log can be fully reviewed in LCD keypad
- * Quick help key feature for common used function
- * Door chime
- * Quick arming
- * 15 user and 1 ambush password
- * Easy key for home or away arming mode
- * Remote control arm/disarm (optional)
- * Remote control Panic/Emergency (optional)
- System restore to original status & setting after power recovery or any unexpected operation (due to lightning)
- * Surge protection for all zone and phone line terminals
- * Overload protection for Siren & Aux output
- * Walk test

Zone:

- * Max 12 zones
- * EOL against zone wire tampering
- * Zone sensitivity adjustment
- * Digital signal processing to reduce false alarm
- * Fully Programmable to be different application e.g. Keyswitch, Instant/delayed, Pre-alarm or 24-hour (Panic, Fire or Emergency) zone

Central Monitoring Station (CMS)

- * Contact ID
- * 2 telephone CMS numbers supported
- * Alternative or double reporting to CMS
- * Daily test
- * Manual test with confirmation feedback for successful reporting
- * Ambush/hostage code

Personal Telelphone Reporting

- * 4 phone numbers supported
- * Fax machine tel line sharing by double call-in feature
- * Call user(s) right after alarm trigger
- * User call in control with valid password
- * Phone hang up after 5 invalid password entry w/ LCD indication
- * Zone bypass through phone
- * Report current arming status
- * Report current triggered zone (Tone or Voice with SE voice module)
- * Report AC Loss (Tone or Voice with SE voice module)
- * Sound monitoring through phone (with SE voice module)

Home Automation

- * 2 built in automation points
- * Check status through phone
- * Control through keypad or phone
- * 2 way control through additional switch
- * Automation with 14 different conditions (e.g. alarm status, different types zone triggering)