

Variable Speed Drive

TOSVERT VF-S15 STANDARD/PREMIUM





Simple compact and high performance drive

The new Toshiba VF-S15, standard general purpose drive, is designed for controlling wide range of variable torque and constant torque applications such as pumps, fans, lifts, conveyors, machine tool, food processor and mixers as well as for process control in various types of industries.

Also, PM motor drive for energy saving and a wide variety of communication options are available for all needs.(Premium model)



感電、火災のおそれがあります。

後説明書の注意事項を誘むこと。 電中及び電源遮断後 1 5分以内は端子カバーを関けないこと。



STO complied (Premium model)

Safe Torque Off function is for insulating the output reliability in the event of an emergency and can simplify the system and reduce the cost. (IEC standard)




My function (Premium model)

Logic sequence function inside



PM motor drive (Premium model)

Permanent magnetic motor (SPM, IPM) can be driven for energy saving purpose



Energy saving
Reducing the energy consumption for variable torque application (FAN and Pump)



Installation

The bottom wire protection cover can be removed by one push opener. I/O terminal door cover can be locked for safety.



Setup Dial

Easy to operate for parameter writing and monitoring with setup dial



Dual rating

Both constant torque application and high current variable torque application can be operated




Easy Key

Up to 32 kinds of parameter can be stored for one group




Parameter writer (Optional)

VFS15 can be programmed parameters without power connection



Long-life design

10 years life design by using long life capacitors



Communications

Ethenet/IP Modbus TCP EtherCAT Profibus-DP



Item		Specification										
Input voltage		3-phase 240V										
Applicable motor (kW)		0.4	0.75	1.5	2.2	4.0	5.5	7.5	11	15		
Туре		VFS15										
Rat	Form	2004PM-W	2007PM-W	2015PM-W	2022PM-W	2037PM-W	2055PM-W	2075PM-W	2110PM-W	2150PM-W		
	Capacity (kVA) (Note 1)	1.3	1.8	3.0	4.2	6.7	10.5	12.6	20.6	25.1		
	Rated output/current (A) (Note 2)	3.3	4.8	8.0	11.0	17.5	27.5	33.0	54.0	66.0		
	Output voltage (Note 3)	3-phase 200V to 240V										
	Overload current rating	150%-60 seconds, 200%-0.5 second										
Power supply	Voltage-frequency (Allowable fluctuation)	3-phase 200V to 240V - 50/60Hz (170V to 264V (Note 4), frequency ±5%)										
	Required capacity (kVA) (Note 5)	1.4	2.5	4.3	5.7	9.2	13.8	17.8	24.3	31.6		
Protection degree (IEC60529)		IP20										
Coolii	ng method	Self-cooling Forced air-cooled										
Built-in filter		Basic filter										

Item		Specification													
Input voltage		1-phase 240V				3-phase 500V									
Applicable motor (kW)		0.2	0.4	0.75	1.5	2.2	0.4	0.75	1.5	2.2	4.0	5.5	7.5	11	15
	Туре		VFS15S					VFS15							
ating	Form	2002PL-W	2004PL-W	2007PL-W	2015PL-W	2022PL-W	4004PL-W	4007PL-W	4015PL-W	4022PL-W	4037PL-W	4055PL-W	4075PL-W	4110PL-W	4150PL-W
	Capacity (kVA) (Note 1)	0.6	1.3	1.8	3.0	4.2	1.1	1.8	3.1	4.2	7.2	10.9	13.0	21.1	25.1
Rat	Rated output current (Note 2)	1.5	3.3	4.8	8.0	11.0	1.5	2.3	4.1	5.5	9.5	14.3	17.0	27.7	33.0
	Rated output voltage (Note 3)		3-phase 200V to 240V				3-phase 380V to 500V								
	Overload current rating	15	150%-60 seconds, 200%-0.5 second				150%-60 seconds, 200% -0.5 second								
Power supply	Voltage-frequency (Allowable fluctuation)	1-phase 200V to 240V – 50/60Hz (170V to 264V ^(Note 4) , frequency ±5%)					3-phase 380V to 500V - 50/60Hz (323V to 550V ^(Note 4) , frequency ±5%								
Po	Required capacity (kVA) (Note 5)	0.8	1.4	2.3	4.0	5.4	1.6	2.7	4.7	6.4	10.0	15.2	19.5	26.9	34.9
Protection degree (IEC60529)		IP20					IP20								
Cooli	Cooling method		Self-cooling Forced air-cooled				Forced air-cooled								
Built-in filter		EMC filter					EMC filter								
Note 1: Capacity is calculated at 220V for the 240V models at 440V for the 500V models															

Note 1. Capacity is Cardinated at 220 v1 or the 240 v1 modes; at 440 v1 or the 500 v1 modes. Note 2: Indicates rated output current setting when the PWM carrier frequency (parameter F300) is 4kHz or less.

Note 3: Maximum output voltage is the same as the input voltage.

Note 4: At 1809-264V for the 240V models, at 342V-550V for the 500V models when the inverter is used continuously (load of 100%).

Note 5: Required power supply capacity varies with the value of the power supply side impedance (including those of the input reactor and cables).

Voltage										
Class	Motor	VF-S15								
l	(kW)	W	Н	D	W1	H1	(kg)			
3-phase	0.4	72		120	60		0.9			
240V	240V 0.75		130		00	121.5	1.0			
	1.5	105	130	130	93	121.5	1.4			
	2.2				93		1.4			
l	4.0	140	170	150	126	157	2.2			
l	5.5	150	220	170	130	210	3.5			
l	7.5						3.6			
	11	180	310	190	160	295	6.8			
	15						6.9			
1-phase	0.2			101	131	121.5	0.8			
240V	0.4	72		120	60		1.0			
	0.75		130	135	00		1.1			
	1.5	105		150	93		1.6			
l	2.2	105			93		1.6			

Voltage	Applicable		Approx.					
Class	Motor		weight					
	(kW)	W	W H D W1 H1					
3-phase	0.4						1.4	
500V	0.75	107	130	153	93	121.5	1.5	
	1.5						1.5	
	2.2	140	170	160	126	157	2.4	
	4.0	140					2.6	
	5.5		220	170	130	210	3.9	
	7.5	150	220	170	130	210	4.0	
	11	180	310	190	160	295	6.4	
	15	100	310	130	100	233	6.5	

W: width H:heigh D: depth W1: Mounting dimension(horizontal) H1: Mounting dimension (vertical)

To users of our inverters: Our inverters are designed to control the speeds of three-phase induction motors for general industry.

Precautions

*Please read the instruction manual before installing or operating the inverter unit.

*This product is intended for general purpose uses in industrial application. It cannot be used applications where may cause big impact on public uses, such as power plant and railway, and equipment which endanger human life or injury, such as nuclear power control, aviation, space flight control, traffic, safety device, amusement, or medical.

It may be considerable whether to apply, under the special condition or an application where strict quality control may not be required. Please contact our headquarters, branch, or local offices printed on the front and back covers of this catalogue

When exporting Toshiba Inverter separately or combined with your equipment, please be sure to satisfy the objective conditions and inform conditions listed in the export control policies, so called Catch All restrictions, which are set by the Ministry of Economy, Trade and Industry of Japan, and the appropriate export procedures must also be taken.

*Please use our product in applications where do not cause serious accidents or damages even if product is failure, or please use in environment where safety equipment is applicable or a backup circuit device is provided outside the system.

*Please do not use our product for any load other than three-phase induction motors.

*None of Toshiba, its subsidiaries, affiliates or agents, shall be liable for any physical damages, including, without limitation, malfunction, anomaly, breakdown or any other problem that may occur to any apparatus in which the Toshiba inverter is incorporated or to any equipment that is used in combination with the Toshiba inverter. Nor shall Toshiba, its subsidiaries, affiliates or agents be liable for any compensatory damages resulting from such utilization, including compensation for special, indirect, incidental, consequential, punitive or exemplary damages, or for loss of profit, income or data, even if the user has been advised or apprised of the likelihood of the occurrence of such loss or damages.

For further information, please contact your nearest Toshiba Representative or International Operations-Producer Goods. The information in this brochure is subject to change without notice.

TOSHIBA INDUSTRIAL PRODUCTS SALES CORPORATION

Global Industrial Products Business Unit

1-1, Shibaura 1-Chome, Minato-ku, Tokyo 105-8001, Japan.

Tel: +81-3-3457-8128, Fax: +81-3-5444-9252

http://www.tips.toshiba.com.au/