

EMMA-812A/825A

DVD Player/Cassette/ AM/FM Tuner with Amplifier



EMIX All in one amplifier is an amplifier built-in with background music source. The unit comprises a DVD player, a digital controlled FM/AM tuner, and a recordable cassette player in a compact 3U-height. It comes with a pair of earpieces. It is typically used in shops, supermarkets, restaurant, bars, canteens, showrooms, gymnasiums and others places where BGM creates the right atmosphere. The unit can be connected for additional amplifier by using out link.

Features

- > Stereo source unit for background music
- > RS232 provided for control system
- > CD Player for DVD/MP3/CD-RW
- > FM/AM with 20 preset and digital control
- > Built in 2 microphone inputs with individual volume control and chime generator
- > Aux input and output for additional amplifier and recording features
- > Bass, treble and master volume control
- > Two mic/line inputs, one priority input (Mic 1 > Mic 2)
- > Video output provided

Model	EMMA-812A	EMMA-825A
Rated Output	120W	250W
Output Regulation	Less than 5%	
Speaker Output	Balanced 4Ω, 70V, 100V	
AUX Out	600Ω, 1V (0dBV)	
Input	MIC 1,2: 600Ω, 2.5mV (-52dBV), unbalanced AUX: 10kΩ, 150mV (-17dBV), unbalanced	
Frequency Response	MIC 100Hz~10kHz; AUX 100 Hz~16kHz	
Distortion	Less than 0.5% at 1kHz, 1/3 rated power	
Signal to Noise Ratio	MIC 1,2: 66dB AUX: 70dB	
Tone	Bass: ±10 dB at 100Hz Treble: ±10 dB at 10kHz	
Protection	AC fuse, DC voltage, overload and short circuit	
Muting Function	MIC 1 overrides other input signals with 0~-30dB attenuation	
Power Requirements	AC220-240V / 50-60Hz	
Dimensions(mm)	420 x 400 x 132	
Power Consumption	250W	500W
Net Weight	15.8kg	17.9kg

Rear View



ALL IN ONE MIXING AMPLIFIER