



Kodio

TRDX-740

DMX 136CH Lighting Controller

- * 136 channel DMX output and MIDI in, CF memory card for programs
- * Each control via LCD display, External power supply
- * Simultaneous and independent control of scanner and parcan section.
- * 128 channel for 8 scanners with up to 16 channels.
- * 12 pages and each composed 8 programmable scenes.
- * 8 chases and 99 steps.
- * Programmable speed and fade time
- * Patch possibility, Joystick with fine mode and 4 step buttons.
- * 8 channel dim faders with 1 master fader
- * 12 pages and each composed 6 programmable scenes
- * 6 chases and each with 99 steps
- * Speed & Tap-sync and audio fader
- * Step function, standby and full on Mode and Step Change, Full on, Blackout and etc.

Specification DMX 136CH Lighting Control Console

Item	Description
Remote Fog Machine	5 pin Din
Remote Audio Input	1/4 Stereo Jack
DMX Output	3 pin XLR
DMX Select Polarity	Switch DMX Polarity
MIDI Thru / IN / OUT	4pin Din
CF Card Socket	32MB
Power Supply	DC9V~12V / 600mA
Power Dissipation	Max 6W
Temperature	Operating 5°C ~ 70°C
Humidity	Operating 5% ~ 90%
Dimension	482*178*80 mm
Weight	3.6kg