

MT-200

MATCHING TRANSFORMER

The MT-200 is a matching transformer for the HX-5 series and HX-7 series speaker systems, and can be used both indoors and outdoors.



Order no: MT-200 EU

Specifications

Rated input	200 W
Tappings	Primary Side: 100 V line: 50 Ohm (200 W), 83 Ohm (120 W), 167 Ohm (60 W) 70 V line: 25 Ohm (200 W), 50 Ohm (100 W), 83 Ohm (60 W), 167 Ohm (30 W) Secondary Side : 8 Ohm
Dimensions (W x H x D)	164 x 141 x 129 mm
Dimensions (ø x D)	x 129 mm

MT-200

MATCHING TRANSFORMER

Appearance

When the matching transformer is installed on the HX-5 series rear mounting plate, the optional HY-WM1 series and HY-CW1 series Speaker Mounting Brackets, and HY-ST1 Speaker Stand Adapter cannot be used. When mounting the matching transformer to the HX-7 series, an optional HY-MT7 Matching Transformer Adapter is required.

