

PTZ & DVR KEYBOARD CONTROLLER

KB-H6



Features:

- Professional PTZ controller for CCTV System
- LCD display with error indication, easy for operation and installation
- Precision Joystick allows accurate control for speedome cameras
- Long distance control: 1200m (RS485, 0.5mm twisted pair cable)
- Nominal control up to 32 PTZ cameras, 16 DVRs (H6K series)
- Maximum control up to 255 PTZ cameras & 254 H6K DVRs with data distributor
- Multiple Keyboard in Master/Slave combination
- Multiple protocol output including Pelco-P and Pelco-D
- Adjustable baud rate
- 3D / 3-Axis Joystick, direct control DVR & Speedome

Specifications:

Model	KB-H6
Communication	Master: RS485 (2400bps, 4800bps, 9600bps) Slave: RS232 (2400bps, 4800bps, 9600bps) LAN: (3 AXIS WEB only) (2400bps, 4800bps, 9600bps)
Joystick Power Consumption	DC 12V, 110mA, (3-Axis, zoom in/out available)
Display Type	16 x 2 character LCD, with blue backlight
Key Type	PC key board button
Key Board Connection Type	RJ45 8 pin modular cable
Junction Box Connector	Master: Terminal block Slave: 9 pin D-SUB connector, 8 pin modular
Humidity	10% - 70% non condensing
Web	-
Dimension (mm)	140(W) x 185(H) x 365(D)
Power Supply	12VDC, 500mA
Weight	1.2kg

Note: Specifications may change without prior notice