

BNC TO VGA (TV-PC) CONVERTER

APPLICATION

❖ Converts most LCD monitors into security monitors. The converter allows displays with a VGA input to display video signals coming from a BNC connector.

PRODUCT FACTS

- ❖ NTSC or PAL compatible.
- ❖ Video input auto-configure.
- ❖ Adjustable functions: color, contrast, tint and brightness.

PRODUCT CODE

- ❖ BNC-VGA



TECHNICAL DATA

Input signal	Composite video 1Vp-p 75ohm BNC jack
---------------------	--------------------------------------

Output signal	VGA: 0.7 Vp-p RGB, 15 pin female D-sub
----------------------	--

Current consumption	200mA@5VDC
----------------------------	------------

Maximum resolution	NTSC: 720x480, PAL: 720x576
---------------------------	-----------------------------

Power source	500mA@5VDC, 2.5mm jack (adapter included)
---------------------	--

Dimensions	110mm(length) x 56mm(width) x 36mm(height)
-------------------	--

Weight	7.8-oz (220g)
---------------	---------------
