

IMC GASOLINE GENERATOR (ATH-SERIES)



ATH3000



ATH7500E

MODEL				ATH3000	ATH7500E	
ENGINE	Model (HONDA)			GX-160	GX-390	
	Displacement		cc	163	389	
	Rate	3,000rpm	HP	3.8	9.4	
	Horse Power	3,600rpm		4.8	11.7	
	Ignition system			Transistor		
	Oil alert system			YES		
	Starting system			Recoil (OP: Electric)		
GENERATOR	Type			Self-exciting 2-pole, field rotation type		
	Voltage regulation system			AVR		
	Phase			Single		
	AC output	Rated	50Hz	KVA	2.0	5.0
			60Hz		2.3	5.5
		Maximum	50Hz		2.4	6.1
			60Hz		2.9	7.2
	Rated voltage			V 220, 110/220 (60Hz only)		
	DC output			V-A 12V 8.3A		
	Rated Power Factor			Cos Ø 1.0		
SET	Fuel tank capacity			l	15	25
	Dimensions	Length	mm	600	710	
		Width		435	540	
		Height		470	570	
	Weight			kg	47	80.5
	4 - wheel kit			OP		
	Sound level (dB At 7m)			50Hz	63	70
				60Hz	66	72
Continuous Operation time (hr)			50Hz	12.8	8.0	
			60Hz	11.8	6.0	



- Product feature:**
- Large air filter
 - Exhaust muffler.