# Voltage Detectors

### Measuring instruments of low voltage

## 635 IRP-400 Phase/Rotation Indicator

#### Optical

Used to check the direction of the rotating magnetic field in the three-phase system, the phase rotation and the direction of motor rotation.

The direction of motor rotation (direction of rotation) is detected by placing the IRP-400 on the motor and aligning it with the drive shaft with no need to connect any probes

A durable, lightweight and reliable device, ideal for electrical work with three-phase motors and systems. Includes different types of probes for any possible application.



Operating voltage: 120 V ~ 400 VAC Current consumption: ≤20 mA Frequency range: 2 Hz ~ 400 Hz

Non-contact rotating field indication function

Operating temperature: 0 °C a +40 °C Operating altitude: 2000 m Category: CAT III 600 V Certificates: CE, RoHS Power supply: 3 x 1.5 V AA batteries

Dimensions: 128 × 70 × 30 mm

Weight: 168 g

Supplied with a nylon case for transport and storage. According with standards EN61010-1, EN61010-2-032, EN61326 and IEC 62321.



63 sofamel







Accessories included.

