

# DC-AC INVERTER

Item No.	Description	Picture
<b>PURE SINE WAVE SERIES - 300W</b>		
NC-300-S	<p>DC 12V/24V TO AC 230V 300W continuous power inverter 600W Peak Power No Load Current Draw: &lt; 0.5A Efficiency: &gt; 87% Pure sine wave output Input Voltage : 10V-15V/21V-30V Frequency: 50HZ<math>\pm</math>2 Low battery alarm:10.5V<math>\pm</math> 0.3V,21<math>\pm</math>0.5V Low battery shut down: 10V<math>\pm</math>0.5V 20V DC<math>\pm</math>0.5V Over voltage shut down: 15.5V<math>\pm</math>0.5V or 30.5V<math>\pm</math>0.5V Over load shut down :360W over 10 seconds Over heating shut down&gt;75 Over Thermal :shut down the output Short Circuit: fuse Working Temperature: Between -10 and +50 Working Humidity: 20% ~ 90%RH non-condensing Storage Temperature : Between -30 and +70 Dimension: 150*130*52mm Weight : 1.2KG Packing : 12pcs/ctn</p>	 