



## TRDX-220

### DMX 24CH Lighting Console

- \* 512 DMX channel, Including 24 individual channels.
- \* Output Unlimited scenes can be created using 24 faders.
- \* Manually 4 pages of programs, each page holds up to 24 programs.
- \* Each program consists of up to 1000 steps (recorded scenes).
- \* The programs can be activated by Audio / Speed slider / Standard beat, and etc.
- \* Select one or more programs at a time.
- \* Send MIDI file dump and receive MIDI file dump.
- \* Blackout master Record code enables to protect the program from intentional acts.
- \* DMX polarity selectable for the DMX cable.
- \* Mode and Step Change, Full on, Blackout and etc.
- \* Power failure memory.

### Specification DMX 24Ch Lighting Console

Item	Description
Remote Fog Machine	5 pin Din
Remote Audio Input	1/4 Stereo Jack
DMX Output	3 pin XLR
DMX Select Polarity	Switch DMX Polarity
MIDI Thru / IN / OUT	4pin Din
Power Supply	DC12V~20V / 500mA
Power Consumption	Max 6W
Temperature	Operating 5°C ~ 70°C
Humidity	Operating 5% ~ 90%
Dimension	482*264*80 mm
Weight	5kg