



SS-6401 has 4 BGM source input via RCA jack with mono output suitable for PA system. It has line balancing circuitry which provides equal output level no matter which input is selected, as different BGM sources have different output levels. This avoids the trouble of adjusting mixer volume whenever a different source is changed.

Features

- ❑ 4 input sources; Cassette, CD, Tuner and AUX.
- ❑ Input level balancing circuit for constant output level for different types of BGM sources.

Technical Specifications

Input Voltage	24C DC ; 0.3A
Consumption	0.15A
Input level / Imp (max input)	CD : 2V / 47K Ohm Tuner : 600 mV / 10 K Ohm Cassette : 500 mV / 10 K Ohm Aux : 1.25V / 20 K Ohm
Input Connection	RCA mono
Output	RCA mono, 1V 600 Ohm
Gain (max)	CD : -6 dB / Tuner : 4 dB Cassette : 6 dB / Aux : -2 dB
Selection	Daisy chain
Dimension (W x H x D)	482 x 44 x 180 mm
Weight	1.8 kg