



# AREX SOLAR WALL LIGHT LED

## 3.2W –AR-SWL- 3.2W

### Products Information:

Arex Solar Wall Light LED comes into three different modes:

**MODE A:** Automatically ON at the dusk (<30 lux) and remains 20% bright, up to 5hours after which it turns off.

**MODE B:** Automatically ON to full brightness (400lm) when motion is detected in the range 2-6 metres and then turns to 3% brightness in 20 seconds of no motion.

**MODE C:** Automatically ON to full brightness (400lm) when motion is detected in the range 2-6 metres and then turns off in 30seconds when no motion.

### Products Features:

- Zero Electricity,
- PIR Detection,
- Cordless
- Solar powered,
- Light ON/OFF automatically

### Application Area:

- House, garden, entrance, pathway
- Others

## PRODUCTS SPECIFICATIONS

|                               |                     |                          |  |
|-------------------------------|---------------------|--------------------------|--|
| <b>Model:</b>                 | <b>AR-SWL-3.2W</b>  | <b>Product Code:</b>     | <b>1023000003</b><br><b>1023000004</b> |
| <b>Wattage:</b>               | 3.2W                | <b>Led Quantity:</b>     | 30 pcs                                 |
| <b>Supply Voltage (V):</b>    | AC 2.8V-4.2V        | <b>Rated Lumen:</b>      | 400 lm                                 |
| <b>CCT:</b>                   | 3000K<br>6500K      | <b>Lumen Efficiency:</b> | 125lm/w                                |
| <b>CRI:</b>                   | ≥80                 | <b>Beam Angle:</b>       | 120 <sup>0</sup>                       |
| <b>Light Source:</b>          | SMD 2835            | <b>Rated Life(L70):</b>  | 35000 Hours                            |
| <b>Operating Environment:</b> | From -20°C to +55°C | <b>Barcode:</b>          | 9 555106309836<br>9 555106309843       |