





# **AREX SOLAR STREET LANTERN LED BLACK - AR-SSL- 40W**

### **Working Mode:**

- i. Smart Button: ON/OFF
- ii. Switch/Confirm
- iii. Constant Lighting Mode

Automatically turns on at dusk and remains 50% brightness









#### iv. PIR Sensor Mode

Automatically turns on to full brightness when motion is detected in the range ≤15 meter and then dim 5% brightness in 20 seconds of no motion.



## v. Constant Lighting & PIR Sensor Mode

Automatically turns on at dusk and remains 50% brightness up to 5 hours, then turns to PIR sensor mode.



## **PRODUCTS SPECIFICATIONS**

Model:	AR-SSL-40W	Product Code:	1023000015
Wattage (W):	40W	Led Quantity:	21 pcs
Input Voltage (V):	9.0V – 12.0V	Rated Lumen:	6,000 lm
Working currents(A):	3500mA	Lumen Efficiency:	150lm/w
CCT:	6000K	Beam Angle:	140 <sup>0</sup> X70 <sup>0</sup> -TPIII
CRI:	≥80	Rated Life(L70):	35,000 Hours
Light Source:	SMD 2835	Barcode:	9 555106308976
Operating Environment:	From -20°C to +50°C		

Arex Solar Street Lantern Led Black - SSL-40W data sheet

Last update: August 2020