

Product Code	Description
W8211ETV	1 Gang Broadband Socket Outlet (F-Connector) (Module)



W8211ETV






















Product back view

### Technical Specification

- One Deco module size
- For 75-ohm coaxial cable
- Cable centre/inner conductor needs to be solid wire, not stranded
- Dimensions: 40 x 23 x 10 mm (HxWxD)
- Mounting box: >35 mm\*
  - R1150, flush mounting, plastic (80 x 80 x 48.4 mm) (WxHxD)
  - M1247, flush mounting, metal (79 x 73 x 47 mm) (WxHxD)

\*Allow room for bend radius of cable

Product Code	Colour
W8211ETV	 White
W8211ETV-SBL	 Matt Black (SBL)
W8211ETV-ST	 Charcoal Black (ST)
W8211ETV-MSB	 Matt Silver Black (MSB)
W8211ETV-MSL	 Matt Silver (MSL)
<i>For other colours, please contact T&amp;J Sales representative</i>	

Adapter plate for Deco module					
Series	Product Code				
	1 gang adapter plate	2 gang adapter plate	3 gang adapter plate		
deco	W1111 	W1112A 	W1113 		
infnit	HC1231 	HC1232 			
HARMONY	EA1231 	EA1232 			
minimalist	EB1231 	EB1232 			
radiance	K1231-D 	K1201-D 			
Titanium	GC1231 	GC1221 			
Ultimate	G1231 	G1221 