

LED Wave Downlight



Product Description	Product Code	Colour Temperature	Luminous Flux (Lm)	Power Factor	Input Power(W)	Beam angle(°)	CRI	Driver	Product Size(mm)	Cut Out Size(mm)
LED 12W 3000K WAVE DOWNLIGHT	N03E0-1019	3000K	1030	>0.9	12W	90°-100°	>80	Integrated	φ 145 x 65.8	φ120-130
LED 12W 4000K WAVE DOWNLIGHT	N03E0-1020	4000K	1080	>0.9	12W	90°-100°	>80	Integrated	φ 145 x 65.8	φ120-130
LED 12W 6000K WAVE DOWNLIGHT	N03E0-1021	6000K	1080	>0.9	12W	90°-100°	>80	Integrated	φ 145 x 65.8	φ120-130
LED 14W 3000K WAVE DOWNLIGHT	N03E0-1022	3000K	1200	>0.9	14W	90°-100°	>80	Integrated	φ 174 x 68.5	φ145-155
LED 14W 4000K WAVE DOWNLIGHT	N03E0-1023	4000K	1260	>0.9	14W	90°-100°	>80	Integrated	φ 174 x 68.5	φ145-155
LED 14W 6000K WAVE DOWNLIGHT	N03E0-1024	6000K	1260	>0.9	14W	90°-100°	>80	Integrated	φ 174 x 68.5	φ145-155
LED 20W 3000K WAVE DOWNLIGHT	N03E0-1025	3000K	1780	>0.9	20W	90°-100°	>80	Integrated	φ 244 x 84.5	φ195-210
LED 20W 4000K WAVE DOWNLIGHT	N03E0-1026	4000K	1880	>0.9	20W	90°-100°	>80	Integrated	φ 244 x 84.5	φ195-210
LED 20W 6000K WAVE DOWNLIGHT	N03E0-1027	6000K	1880	>0.9	20W	90°-100°	>80	Integrated	φ 244 x 84.5	φ195-210
LED 25W 3000K WAVE DOWNLIGHT	N03E0-1028	3000K	2230	>0.9	25W	90°-100°	>80	Integrated	φ 244 x 84.5	φ195-210
LED 25W 4000K WAVE DOWNLIGHT	N03E0-1029	4000K	2350	>0.9	25W	90°-100°	>80	Integrated	φ 244 x 84.5	φ195-210
LED 25W 6000K WAVE DOWNLIGHT	N03E0-1030	6000K	2350	>0.9	25W	90°-100°	>80	Integrated	φ 244 x 84.5	φ195-210