



RC-CST024-W/4

Ranger 4CH Fix Code Smart Remote



RANGER



Support for two-way wireless detectors Wireless Gate magnetic, And wired gate magnets.



Support Open Door, Close real-time APP information notification, phone SMS notification, call notification.



Supports automatic door opening/closing, timed automatic door opening/closing, and scene control linkage.

*All image and specification is subject to change without prior notice.



*Come with 3 transmitter & 1 receiver (with cover)

Technical Data	RC-CST024-W/4
Working Sensitivity & Distance	-122DB, Open the distance 3000M (With the T3000)
Supports APP	SmartLife / Tuya / WIFISMARTCONTROL
Wifi Frequency	2.4G IEEE 802.11b
Remote control Frequency	433MHZ/330MHZ Optional (CST15/015 330MHZ CST16/016 433MHZ CST17/017 433MHZ CST22/022 433MHZ)
Remote control IC	TAIWAN SMC5326P/S
Access	2CH/4CH Remote Control
Operating Voltage Current	DC12-40V / AC9-28V ; DC12V 60MA MAX

Ordering Info

Model

RC-CST024-W/4